Schémas de câblage
Cabling

Références/*PN*	Borniers *Blocks*	Signalaux *Signals*	Connecteurs *Connectors*
MQD8000SM *MQPCX800F*	1	Rouge/*Red*	1
	2	Vert/*Green*	2
	3	Bleu/*Blue*	3
	4	ID Bit 2	4
	5	Gnd	5
	6	Masse rouge/*Ground red* + générale/*overall*	6
	7	Masse vert *Ground green*	7
	8	Masse bleu *Ground blue*	8
	9	+ 5V DC	9
	10	Masse/*Ground* SV + SH	10
	11	ID Bit 0	11
	12	ID Bit 1	12
	13	Synchro Horizontale	13
	14	Synchro Verticale	14
	15	ID Bit 3	15
MQD1130M *MQPCX910* *MQPCX911* *MQPCX402*	1	Audio droit/*right*	Pt chaud RCA *Life RCA*
	2	Masse droit *Ground right*	Masse RCA *Ground RCA*
	3	Audio gauche/*left*	Pt chaud RCA *Life RCA*
	4	Masse gauche *Ground left*	Masse RCA *Ground RCA*
	5	Video	Pt chaud BNC *Life BNC*
	6	Masse/*Ground* video	Masse BNC *Ground BNC*
MQD7072M *MQPCX100*	1	V bus 5V	1
	2	D -	2
	3	D +	3
	4	Masse/*Ground*	4
	5	Masse générale *Ground*	Masse USB *Ground USB*
MQD13944M *MQPCX13944*	1	TPB -	1
	2	TPB +	2
	3	TPA -	3
	4	TPA +	4
	5	Masse générale *Ground*	Masse *Ground*
MQD13946M *MQPCX13946*	1	Bus power	1
	2	Masse/*Ground*	2
	3	TPB -	3
	4	TPB +	4
	5	TPA -	5
	6	TPA +	6
	7	Masse générale *Ground*	Masse *Ground*

Références/*PN*	Borniers *Blocks*	Signalaux *Signals*	Connecteurs *Connectors*
MQD1000KM *MQPCX910-911*	1	Video	Pt chaud BNC *Life BNC*
	2	Masse/*Ground*	Masse/*Ground*
MQD1100M *MQPCX401-411*	1	Video	Pt chaud RCA *Life RCA*
	2	Masse/*Ground*	Masse/*Ground*
MQD1000KM *MQPCX910-911*	1	Video	Pt chaud BNC *Life BNC*
	2	Masse/*Ground*	Masse/*Ground*
MQD1100KM *MQPCX401-411*	1	Video	Pt chaud RCA *Life RCA*
	2	Masse/*Ground*	Masse/*Ground*
MQD2000M *MQPCX430*	1	Y Luminance	3
	2	Masse/*Ground* Y	1
	3	Masse/*Ground*	Masse/*Ground* Mini Din
	4	C Chrominance	4
	5	Masse/*Ground* C	2
MQD3000M *MQPCX402*	1	Audio droit/*right*	Pt chaud RCA *Life RCA*
	2	Masse droit *Ground right*	Masse RCA *Ground RCA*
	3	Audio gauche/*left*	Pt chaud RCA *Life RCA*
	4	Masse gauche *Ground left*	Masse RCA *Ground RCA*
MQD3006M *MQPCX635*	1	Masse générale *Ground overall*	Masse Jack *Ground Jack*
	2	Audio gauche/*left*	Pt chaud RCA *Life RCA*
	3	Audio droit/*right*	Pt chaud RCA *Life RCA*
MQD3003M *MQPCX350* *MQPCX351*	1	Masse générale *Ground overall*	Masse Jack *Ground Jack*
	2	Audio gauche/*left*	Pt chaud RCA *Life RCA*
	3	Audio droit/*right*	Pt chaud RCA *Life RCA*
MQD4350M *MQPCX438*	1	-	1
	2	-	2
	3	-	3
	4	-	4
	5	-	5
	6	-	Masse DIN 5b Ground DIN 5p
MQD1103M *MQPCX403YUV*	1	Y	Pt chaud RCA *Life RCA*
	2	Masse/*Ground* Y	Masse RCA *Ground RCA*
	3	U	Pt chaud RCA *Life RCA*
	4	Masse/*Ground* U	Masse RCA *Ground RCA*
	5	V	Pt chaud RCA *Life RCA*
	6	Masse/*Ground* V	Masse RCA *Ground RCA*
MQD3140M *MQPCX403*	1	Audio droit/*right*	Pt chaud RCA *Life RCA*
	2	Masse droit *Ground right*	Masse RCA *Ground RCA*
	3	Audio gauche/*left*	Pt chaud RCA *Life RCA*
	4	Masse gauche *Ground left*	Masse RCA *Ground RCA*
	5	Video	Pt chaud RCA *Life RCA*
	6	Masse/*Ground* video	Masse RCA *Ground RCA*
MQD4000F-M *MQPCX777F* *MQPCX777M*	1	Masse/*Ground*	1
	2	Pt chaud XLR *Life + XLR*	2
	3	Point froid XLR *Life - XLR*	3
MQD1030M *MQPCX403*	1	Audio droit/*right*	Pt chaud RCA *Life RCA*
	2	Masse droit *Ground right*	Masse RCA *Ground RCA*
	3	Audio gauche/*left*	Pt chaud RCA *Life RCA*
	4	Masse gauche *Ground left*	Masse RCA *Ground RCA*
	5	Video	Pt chaud RCA *Life RCA*
	6	Masse/*Ground* video	Masse RCA *Ground RCA*

Schémas de câblage
Cabling

Références/*PN*	Borniers *Blocks*	Masse *Ground*	Signalaux *Signals*	Connecteurs *Connectors*
MQD1240M *MQPCX29DVI*	Recto 1		Hot plug detect	16
	Recto 2		Gnd (+5V)	15
	Recto 3		+5V power	14
	Recto 4		TMDS Data 3+	13
	Recto 5		TMDS Data 3-	12
	Recto 6		TMDS Data 1/3 shield	11
	Recto 7		TMDS Data 1+	10
	Recto 8		TMDS Data 1-	9
	Recto 9		DDC Data	7
	Recto 10		DDC Clock	6
	Recto 11		TMDS Data 4+	5
	Recto 12		TMDS Data 4-	4
	Recto 13		TMDS Data 2/4	3
	Recto 14		TMDS Data 2+	2
	Recto 15		TMDS Data 2-	1
	Verso 1		TMDS Data 0-	17
	Verso 2		TMDS Data 0+	18
	Verso 3		TMDS Data 0/5 shield	19
	Verso 4		TMDS Data 5-	20
	Verso 5		TMDS Data 5+	21
	Verso 6		TMDS clock schield	22
	Verso 7		TMDS clock+	23
	Verso 8		TMDS clock-	24
	Verso 9		Analog sync vertical	8
	Verso 10		Ground	Ground DVI

Références/*PN*	Borniers *Blocks*	Masse *Ground*	Signalaux *Signals*	Connecteurs *Connectors*
MQD1900M *MQPCX19HDMI*	1		TMDS Data 2 +	1
	2	Tresse/*Shield*	Masse/*Gnd* TMDS Data 2 +	2
	3		TMDS Data 2 -	3
	4		TMDS Data 1 +	4
	5	Tresse/*Shield*	Masse/*Gnd* TMDS Data 1	5
	6		TMDS Data 1 -	6
	7		TMDS Data 0 +	7
	8	Tresse/*Shield*	Masse/*Gnd* TMDS Data 0	8
	9		TMDS Data 0 -	9
	10		TMDS clock +	10
	11	Tresse/*Shield*	Masse/*Gnd* TMDS clock	11
	12		TMDS clock -	12
	13		CEC	13
	14		NC	14
	15		SCL	15
	16		SDA	16
	17		Masse/*Gnd* DDC/CEC	17
	18		+ 5 V	18
	19		Detection pt chaud *Detection life*	19
	20	Tresse générale *Shield overall*	Masse générale *Ground overall*	Masse HDMI *Ground HDMI*